



## MC3x Series Technical Accessory Guide





NOTE: MC32 Android configurations to be discontinued 12/2018 - see PMB 3138  
 MC3190 (non-RFID) discontinued 8/2015  
 MC3090-Z (RFID) discontinued 10/2011  
 MC3000/MC3090 (non-RFID) discontinued 1/2011

NOTE: This document is only for general reference. Solution Builder and related PMBs should be used for product availability, pricing, and final solution selection.






\* Zebra does not endorse or specifically recommend any **third-party products, accessories, or hardware**. ZEBRA DISCLAIMS ANY AND ALL LIABILITY, INCLUDING ANY EXPRESS OR IMPLIED WARRANTIES, WHETHER ORAL OR WRITTEN, FOR SUCH THIRD PARTY PRODUCTS, ACCESSORIES, OR HARDWARE. THE CUSTOMER ACKNOWLEDGES THAT NO REPRESENTATION HAS BEEN MADE BY ZEBRA AS TO THE FITNESS OF THE THIRD-PARTY PRODUCTS, ACCESSORIES, OR HARDWARE FOR THE CUSTOMER'S INTENDED PURPOSE.




### Cradles/Charging





Part Number	Picture	Description	Notes	Required Items
CRD-MC33-2SUCHG-01		MC33 Single Slot Charge/Communication Cradle	<ul style="list-style-type: none"> <li>Provides USB support</li> <li>Supports MC33 terminal and spare battery charging</li> <li>Will charge spare battery for MC33 or MC32.</li> <li>Supports fast-charging of MC33 device and MC33 battery:               <ul style="list-style-type: none"> <li>charges 1X battery from 0-90% in about 2 hours vs. 3 hours for standard charging rate.</li> <li>charges 2X battery from 0-90% in about 3.5 hours vs. 5.5 hours for standard charging rate.</li> </ul> </li> <li>LED notification of spare battery charging status.</li> <li>Not compatible for charging MC32 devices.</li> </ul>	<ul style="list-style-type: none"> <li>Power Supply (PWR-BGA12V50W0WW and CBL-DC-388A1-01)</li> <li>AC Line Cord (23844-00-00R).</li> <li>USB Cable (25-124330-01R) for PC connection</li> </ul>
CRD3000-1001RR		Single Slot Cradle	<ul style="list-style-type: none"> <li>Provides Serial/RS232 or USB support</li> <li>Supports terminal and spare battery charging</li> <li>LED notification of spare battery charging status.</li> <li>Serial port not compatible with Android versions of MC32.</li> <li>No communications support when using MC33. Will only serve as a Charge-Only cradle when used with MC33. Does not support fast-charging of MC33.</li> <li>Does not support charging of MC33 spare battery.</li> </ul>	<ul style="list-style-type: none"> <li>Power Supply (PWR-BGA12V50W0WW and CBL-DC-388A1-01)</li> <li>AC Line Cord (23844-00-00R).</li> <li>Also requires 25-63852-01R or 25-68596-01R for host communication.</li> <li>MC32 Battery Adapter (ADP-MC32-CUP0-01) for charging spare MC32 battery.</li> <li>MC33 Cradle Adapter (ADP-MC33-CRDCUP-01) when using with MC33.</li> </ul>





<p>CRD-MC32-100US-01</p>		<p>MC32/MC33 Single Slot Cradle Kit</p>	<ul style="list-style-type: none"> <li>▶Includes adapter for charging MC32 spare battery</li> <li>▶Provides Serial/RS232 or USB support</li> <li>▶Supports terminal and spare battery charging</li> <li>▶LED notification of spare battery charging status.</li> <li>▶Includes PWR-BGA12V50W0WWW and CBL-DC-388A1-01R power supply/line cord, ADP-MC32-CUP0-01 MC3200 Battery Adapter Cup, and 23844-00-00 AC Line Cord</li> <li>▶Serial port not compatible with Android versions of MC32.</li> <li>▶No communications support when using MC33. Will only serve as a Charge-Only cradle when used with MC33. Does not support fast-charging of MC33.</li> <li>▶Does not support charging of MC33 spare battery.</li> <li>▶Energy Star Compliant</li> </ul>	<ul style="list-style-type: none"> <li>▶25-63852-01R or 25-68596-01R for host communication.</li> <li>▶MC33 Cradle Adapter (ADP-MC33-CRDCUP-01) when using with MC33.</li> </ul>
<p>CRD3000-100RES</p>		<p>Single Slot Cradle Kit</p>	<ul style="list-style-type: none"> <li>▶Provides Serial/RS232 or USB support</li> <li>▶Supports terminal and spare battery charging</li> <li>▶LED notification of spare battery charging status.</li> <li>▶Includes PWR-BGA12V50W0WWW, CBL-DC-388A1-01R and 23844-00-00 AC Line Cord</li> <li>▶Energy Star Compliant</li> <li>▶Serial port not compatible with Android versions of MC32.</li> <li>▶No communications support when using MC33. Will only serve as a Charge-Only cradle when used with MC33. Does not support fast-charging of MC33.</li> <li>▶Does not support charging of MC33</li> </ul>	<ul style="list-style-type: none"> <li>▶25-63852-01R or 25-68596-01R for host communication.</li> <li>▶MC32 Battery Adapter (ADP-MC32-CUP0-01) for charging spare MC32 battery.</li> <li>▶MC33 Cradle Adapter (ADP-MC33-CRDCUP-01) when using with MC33.</li> </ul>
<p>CRD-MC32-100INT-01</p>		<p>MC32/MC33 Single Slot Cradle Kit</p>	<ul style="list-style-type: none"> <li>▶Includes adapter for charging MC32 spare battery</li> <li>▶Provides Serial/RS232 or USB support</li> <li>▶Supports terminal and spare battery charging</li> <li>▶LED notification of spare battery charging status.</li> <li>▶Includes PWR-BGA12V50W0WWW (Power Supply), CBL-DC-388A1-01R (DC Line Cord) and ADP-MC32-CUP0-01 (MC32 Battery Adapter Cup)</li> <li>▶Kit usually order by International customers</li> <li>▶Energy Star Compliant</li> <li>▶Serial port not compatible with Android versions of MC32.</li> <li>▶No communications support when using MC33. Will only serve as a Charge-Only cradle when used with MC33. Does not support fast-charging of MC33.</li> <li>▶Does not support charging of MC33 spare battery.</li> </ul>	<ul style="list-style-type: none"> <li>▶23844-00-00R and 25-63852-01R or 25-68596-01R for host communication.</li> <li>▶MC33 Cradle Adapter (ADP-MC33-CRDCUP-01) when using with MC33.</li> </ul>


CRD3000-101RES		Single Slot Cradle Kit	<ul style="list-style-type: none"> <li>•Provides Serial/RS232 or USB support</li> <li>•Supports terminal and spare battery charging</li> <li>•LED notification of spare battery charging status.</li> <li>•Includes PWR-BGA12V50W0WW (Power Supply) and CBL-DC-388A1-01R (DC Line Cord)</li> <li>•Kit usually order by International customers</li> <li>•Energy Star Compliant</li> <li>•Serial port not compatible with Android versions of MC32.</li> <li>•No communications support when using MC33. Will only serve as a Charge-Only cradle when used with MC33. Does not support fast-charging of MC33.</li> <li>•Does not support charging of MC33 spare battery.</li> </ul>	<ul style="list-style-type: none"> <li>•23844-00-00R and 25-63852-01R or 25-68596-01R for host communication.</li> <li>•MC32 Battery Adapter (ADP-MC32-CUP0-01) for charging spare MC32 battery.</li> <li>•MC33 Cradle Adapter (ADP-MC33-CRDCUP-01) when using with MC33.</li> </ul>
PSCMC3100UE (3rd party) *		Portsmith Single Slot Ethernet Cradle	<ul style="list-style-type: none"> <li>•Cradle communicates with the terminal via USB .</li> <li>•Connects to the LAN via a 10/100 mbps Ethernet connection.</li> <li>•Cradle accommodates terminals equipped with standard or extended batteries.</li> <li>•Includes a USB port (mini-A/B) allowing direct connectivity to a host computer or other USB peripherals.</li> <li>•Also includes spare battery charging and supports both standard and extended capacity batteries.</li> <li>•PSAK3100UE kit includes: PSCMC3100UE cradle, USB cable, Ethernet cable, Power Supply, and AC Cord</li> <li>•No communications support when using MC33. Will only serve as a Charge-Only cradle when used with MC33. Does not support fast-charging of MC33.</li> <li>•Does not support charging of MC33 spare battery.</li> </ul>	<ul style="list-style-type: none"> <li>•Portsmith Power Supply #190362-000LF or 190362-002LC</li> <li>•MC32 Battery Adapter (ADP-MC32-CUP0-01) for charging spare MC32 battery.</li> <li>•MC33 Cradle Adapter (ADP-MC33-CRDCUP-01) when using with MC33.</li> </ul>
CRD-MC33-5SCHG-01		MC33 5-Slot Charge-Only ShareCradle	<ul style="list-style-type: none"> <li>•Will charge up to five MC33 units.</li> <li>•Does not charge spare batteries.</li> <li>•Supports fast-charging of MC33: <ul style="list-style-type: none"> <li>- charges 1X battery from 0-90% in about 2 hours vs. 3 hours for standard charging rate.</li> <li>- charges 2X battery from 0-90% in about 3.5 hours vs. 5.5 hours for standard charging rate.</li> </ul> </li> <li>•Can be racked/ mounted in a standard 19inch rack system via the mounting accessory (BRKT-SCRD-SMRK-01)</li> </ul>	<ul style="list-style-type: none"> <li>•DC Line Cord (CBL-DC-381A1-01) and Power Supply (PWR-BGA12V108W0WW)</li> <li>•AC Line Cord (23844-00-00R)</li> </ul>

CRD-MC33-4SC4BC-01		MC33 5-Slot Charge-Only ShareCradle with Spare Battery Charger	<ul style="list-style-type: none"> <li>•Will charge up to four MC33 terminals and four MC33 or MC32 spare batteries.</li> <li>•Supports fast-charging of MC33 devices and MC33 batteries: <ul style="list-style-type: none"> <li>- charges 1X battery from 0-90% in about 2 hours vs. 3 hours for standard charging rate.</li> <li>- charges 2X battery from 0-90% in about 3.5 hours vs. 5.5 hours for standard charging rate.</li> </ul> </li> <li>•Can be racked/ mounted in a standard 19inch rack system via the mounting accessory (BRKT-SCRD-SMRK-01)</li> </ul>	<ul style="list-style-type: none"> <li>•DC Line Cord (CBL-DC-381A1-01) and Power Supply (PWR-BGA12V108W0WW)</li> <li>•AC Line Cord (23844-00-00R)</li> </ul>
CHS3000-4001CR		4-Slot Charge Only Cradle	<ul style="list-style-type: none"> <li>•Charges 4 terminals</li> <li>•Does <u>not</u> charge spare batteries.</li> <li>•Does <u>not</u> support MC3090Z/MC3190Z (RFID) units. Device's back housing and antenna interfere with fit into cradle.</li> <li>•Does not support fast-charging of MC33.</li> </ul>	<ul style="list-style-type: none"> <li>•DC Line Cord (CBL-DC-382A1-01) and Power Supply (PWR-BGA12V108W0WW)</li> <li>•AC Line Cord (23844-00-00R)</li> <li>•MC33 Cradle Adapter (ADP-MC33-CRDCUP-01) - QTY 4 - when using with MC33.</li> </ul>
CRD3000-400CES		4-Slot Charge Only Cradle Kit	<ul style="list-style-type: none"> <li>•Replaces CRD3000-400CR</li> <li>•Charges 4 terminals</li> <li>•Does <u>not</u> charge spare batteries.</li> <li>•Does <u>not</u> support MC3090Z/MC3190Z (RFID) units. Device's back housing and antenna interfere with fit into cradle.</li> <li>•Does not support fast-charging of MC33.</li> <li>•Includes DC Line Cord (CBL-DC-382A1-01), Power Supply (PWR-BGA12V108W0WW), AC Line Cord (23844-00-00R)</li> <li>•Energy Star Compliant</li> </ul>	<ul style="list-style-type: none"> <li>•MC33 Cradle Adapter (ADP-MC33-CRDCUP-01) - QTY 4 - when using with MC33.</li> </ul>
CRD3000-401CES		4-Slot Charge Only Cradle Kit	<ul style="list-style-type: none"> <li>•Replaces CRD3000-401CR</li> <li>•Charges 4 terminals</li> <li>•Does <u>not</u> charge spare batteries.</li> <li>•Does <u>not</u> support MC3090Z/MC3190Z (RFID) units. Device's back housing and antenna interfere with fit into cradle.</li> <li>•Does not support fast-charging of MC33.</li> <li>•Includes DC Line Cord (CBL-DC-382A1-01), Power Supply (PWR-BGA12V108W0WW)</li> <li>•Kit usually order by International customers</li> <li>•Energy Star Compliant</li> </ul>	<ul style="list-style-type: none"> <li>•23844-00-00R</li> <li>•MC33 Cradle Adapter (ADP-MC33-CRDCUP-01) - QTY 4 - when using with MC33.</li> </ul>
CRD-MC33-5SETH-01		MC33 5-Slot Ethernet/Charging ShareCradle	<ul style="list-style-type: none"> <li>•Allows network speeds up to 1 Gb</li> <li>•Will charge up to five MC33 units.</li> <li>•Supports fast-charging of MC33: <ul style="list-style-type: none"> <li>- charges 1X battery from 0-90% in about 2 hours vs. 3 hours for standard charging rate.</li> <li>- charges 2X battery from 0-90% in about 3.5 hours vs. 5.5 hours for standard charging rate.</li> </ul> </li> <li>•Can be racked/ mounted in a standard 19inch rack system via the mounting accessory (BRKT-SCRD-SMRK-01)</li> </ul>	<ul style="list-style-type: none"> <li>•DC Line Cord (CBL-DC-381A1-01) and Power Supply (PWR-BGA12V108W0WW)</li> <li>•AC Line Cord (23844-00-00R)</li> </ul>

CRD-MC33-4SE4BC-01		MC33 5-Slot Ethernet/Charging ShareCradle with Spare Battery Charger	<ul style="list-style-type: none"> <li>▶Allows network speeds up to 1 Gb</li> <li>▶Will charge up to four MC33 terminals and four MC33 or MC32 spare batteries.</li> <li>▶Supports fast-charging of MC33 devices and MC33 batteries: <ul style="list-style-type: none"> <li>- charges 1X battery from 0-90% in about 2 hours vs. 3 hours for standard charging rate.</li> <li>- charges 2X battery from 0-90% in about 3.5 hours vs. 5.5 hours for standard charging rate.</li> </ul> </li> <li>▶Can be racked/ mounted in a standard 19inch rack system via the mounting accessory (BRKT-SCRD-SMRK-01)</li> </ul>	<ul style="list-style-type: none"> <li>▶DC Line Cord (CBL-DC-381A1-01) and Power Supply (PWR-BGA12V108W0WW)</li> <li>▶AC Line Cord (23844-00-00R)</li> </ul>
CRD3X01-4001ER		4-Slot Ethernet/Charging Cradle	<ul style="list-style-type: none"> <li>▶Allows speeds up to 1 Gb</li> <li>▶Uses less power than CRD3000-4001ER with IEEE 802.3az, "EEE" (Energy Efficient Ethernet)</li> <li>▶Charges 4 terminals</li> <li>▶Does <u>not</u> charge spare batteries.</li> <li>▶Does <u>not</u> support MC3090Z/MC3190Z (RFID) units. Device's back housing and antenna interfere with fit into cradle.</li> <li>▶Ethernet connectivity to host</li> <li>▶Ethernet daisy chain support</li> <li>▶USB Host connection to MC3X00</li> <li>▶May require additional driver from support website.</li> <li>▶No communications support when using MC33. Will only serve as a Charge-Only cradle when used with MC33. Does not support fast-charging of MC33.</li> </ul>	<ul style="list-style-type: none"> <li>▶DC Line Cord (50-16002-029R) and Power Supply (PWRS-14000-241R)</li> <li>OR</li> <li>▶DC Line Cord (CBL-DC-382A1-01) and Power Supply (PWR-BGA12V108W0WW)</li> <li>▶AC Line Cord (23844-00-00R)</li> <li>▶MC33 Cradle Adapter (ADP-MC33-CRDCUP-01) - QTY 4 - when using with MC33.</li> </ul>
CRD3X01-401EES		4-Slot Ethernet/Charging Cradle Kit	<ul style="list-style-type: none"> <li>▶Allows speeds up to 1 Gb</li> <li>▶Charges 4 terminals</li> <li>▶Does <u>not</u> charge spare batteries.</li> <li>▶Does <u>not</u> support MC3090Z/MC3190Z (RFID) units. Device's back housing and antenna interfere with fit into cradle.</li> <li>▶Ethernet connectivity to host</li> <li>▶Ethernet daisy chain support</li> <li>▶USB Host connection to MC3000 - does not require additional software on device.</li> <li>▶Includes DC Line Cord (CBL-DC-382A1-01), Power Supply (PWR-BGA12V108W0WW)</li> <li>▶Uses less power than CRD3000-4001ER with IEEE 802.3az, "EEE" (Energy Efficient Ethernet)</li> <li>▶May require additional driver from support website.</li> <li>▶No communications support when using MC33. Will only serve as a Charge-Only cradle when used with MC33. Does not support fast-charging of MC33.</li> </ul>	<ul style="list-style-type: none"> <li>▶AC Line Cord (23844-00-00R)</li> <li>▶MC33 Cradle Adapter (ADP-MC33-CRDCUP-01) - QTY 4 - when using with MC33.</li> </ul>

ADP-MC33-CRDCUP-01		MC33 Adapter Cup to MC30/MC31/MC32 Legacy Cradles	<ul style="list-style-type: none"> <li>▶Allows MC33 to be used with MC30/MC31/MC32 Single Slot and Multi-Slot Cradles</li> <li>▶NOTE: Adapter Cup doesn't provide communications support (USB, Serial, Ethernet). Will only provide charging support.</li> <li>▶Does NOT support fast-charging of MC33. MC33 used in legacy cradles will be charged at standard rate: <ul style="list-style-type: none"> <li>- charges 1X battery from 0-90% in about 3 hours at standard charging rate.</li> <li>- charges 2X battery from 0-90% in about 5.5 hours at standard charging rate.</li> </ul> </li> <li>▶Order one Adapter Cup for Single Slot Cradles and four Adapter Cups for Multi-Slot Cradles.</li> </ul>	
BRKT-SCRD-SMRK-01		MC33 5-Slot ShareCradle Mounting Bracket	<ul style="list-style-type: none"> <li>▶Allows for rack and wall mounting of one MC33 5-Slot ShareCradle, up to four MC33 Single Slot ShareCradles, or up to four MC32/MC33 4-Slot Battery Chargers.</li> <li>▶Bracket can be mounted on standard 19" network rack or on a wall.</li> <li>▶Has cable routing slots and removable power supply tray that stores and conceals power supplies.</li> <li>▶Adjustable tabs &amp; screw mounts for easy hanging/installation.</li> <li>▶Adjustable orientations: <ul style="list-style-type: none"> <li>- 25° High Density (5-Slot Charge Only Cradle)</li> <li>- Horizontal (Single Slot Cradle or 4-Slot Battery Chargers)</li> </ul> </li> </ul>	
KT-136648-01R		Wall Mount Bracket for MC30/MC31/MC32 4-Slot Cradles	<ul style="list-style-type: none"> <li>▶Allows cradle to be mounted on a wall.</li> <li>▶Replaces 8710-050006-01R. Updated design allows additional wall clearance when using CRD3000-4000 cradle and gun version of device.</li> </ul>	CRD3000-4000ER or CHS3000-4000CR
KT-132400-01R		19" Rack Mount Bracket for MC30/MC31/MC32 4-Slot Cradles	<ul style="list-style-type: none"> <li>▶Enables mounting of one 4-Slot Cradle (CRD3000-4000ER or CHS3000-4000CR) to a standard network rack.</li> <li>▶Cradle must first be mounted to Wall Mount Bracket which then attaches to Rack Mount Bracket.</li> <li>▶Bracket hides Power Supply and DC Line Cord</li> </ul>	Wall Mount Bracket (KT-136648-01R)







MNT-MC33-FLCHKT-01		Fork Lift Cradle Kit (un-powered)	<ul style="list-style-type: none"> <li>▶Bracket holds all MC3X00 configurations, except RFID units, for convenient mounting on fork lift.</li> <li>▶Installs on a roll bar or square surface of the forklift and allows the device to be used in landscape or portrait mode.</li> <li>▶Includes RAM 1" diameter ball on back of cradle.</li> <li>▶Does NOT charge MC3X00.</li> <li>▶Kit includes Fork Lift Cradle (MNT-MC33-FLCH-01), RAM Mount Arm (MNT-RAM-B201U), and RAM Mount Base (MNT-RAM-B247U25)</li> </ul>	
MNT-MC33-FLCH-01		Fork Lift Cradle (un-powered)	<ul style="list-style-type: none"> <li>▶Bracket holds all MC3X00 configurations, except RFID units, for convenient mounting on fork lift.</li> <li>▶Installs on a roll bar or square surface of the forklift and allows the device to be used in landscape or portrait mode.</li> <li>▶Includes RAM 1" diameter ball on back of cradle.</li> <li>▶Does NOT charge MC3X00.</li> <li>▶Not compatible with devices with rubber boot attached.</li> </ul>	<ul style="list-style-type: none"> <li>▶RAM Mount Arm for Fork Lift Cradle (MNT-RAM-B201U)</li> <li>▶RAM Mount Base for Fork Lift Cradle (MNT-RAM-B247U25)</li> </ul>
MNT-RAM-B201U		RAM Mount Arm for MC3X00 Fork Lift Cradle	<ul style="list-style-type: none"> <li>▶Used with Fork Lift Cradle (MNT-MC33-FLCH-01)</li> <li>▶RAM Double Sock Arm for 1" ball</li> <li>▶Uses RAM Mount P/N RAM-B-201U</li> </ul>	
MNT-RAM-B247U25		RAM Mount Base for MC3X00 Fork Lift Cradle	<ul style="list-style-type: none"> <li>▶Used with Fork Lift Cradle (MNT-MC33-FLCH-01)</li> <li>▶Attaches to square shaped rail/post of forklift.</li> <li>▶2.5" Max Width Square Rail Base with 1" diameter ball</li> <li>▶Uses RAM Mount P/N RAM-B-247U-25</li> </ul>	






<p>241468 (3rd party) *</p> <p><a href="http://www.proclipusa.com/category/zebra">http://www.proclipusa.com/category/zebra</a></p>		<p>MC33 Holder, Rear Facing Display, Top Hold, No Tilt or Swivel (un-powered)</p>	<ul style="list-style-type: none"> <li>•Holds MC33 Gun, Brick, or Turret Head devices</li> <li>•Rear Facing - Device screen faces away from user to prevent device usage while driving</li> <li>•Fixed Mount - does not tilt or swivel</li> <li>•Mount ready via AMPS hole pattern</li> <li>•Only compatible with MC33 series, except MC33 RFID units.</li> </ul>	<p>Mount on vehicle using ProClip Pedestal or Forklift Mount - see ProClip website</p>
<p>711056 (3rd party) *</p> <p><a href="http://www.proclipusa.com/category/zebra">http://www.proclipusa.com/category/zebra</a></p>		<p>MC33 Holder, Rear Facing Display, Top Hold, with Tilt Swivel (un-powered)</p>	<ul style="list-style-type: none"> <li>•Holds MC33 Gun configurations only</li> <li>•Rear Facing - Device screen faces away from user to prevent device usage while driving</li> <li>•Variable Mount - can be tilted and swiveled and mounted vertically or horizontally.</li> <li>•Mount ready via AMPS hole pattern</li> <li>•Only compatible with MC33 GUN units, except MC33 RFID units.</li> </ul>	<p>Mount on vehicle using ProClip Pedestal or Forklift Mount - see ProClip website</p>
<p>241467 (3rd party) *</p> <p><a href="http://www.proclipusa.com/category/zebra">http://www.proclipusa.com/category/zebra</a></p>		<p>MC33 Holder, Front Facing Display, Top Hold, No Tilt or Swivel (un-powered)</p>	<ul style="list-style-type: none"> <li>•Holds MC33 Gun, Brick, or Turret Head devices</li> <li>•Front Facing - allows user to access screen and keyboard while cradled.</li> <li>•Fixed Mount - does not tilt or swivel</li> <li>•Mount ready via AMPS hole pattern</li> <li>•Only compatible with MC33 units,, except MC33 RFID units.</li> </ul>	<p>Mount on vehicle using ProClip Pedestal or Forklift Mount - see ProClip website</p>



















<p>711040 (3rd party) *</p>		<p>MC33 Holder, Front Facing Display, Top Hold, with Tilt Swivel (un-powered)</p>	<ul style="list-style-type: none"> <li>▶Holds MC33 Gun, Brick, or Turret Head devices</li> <li>▶Front Facing - allows user to access screen and keyboard while cradled.</li> <li>▶Variable Mount - can be tilted and swiveled.</li> <li>▶Mount ready via AMPS hole pattern</li> <li>▶Only compatible with MC33 units, except MC33 RFID units.</li> </ul>	<p>Mount on vehicle using ProClip Pedestal or Forklift Mount - see ProClip website</p>
<p>various (3rd party) *</p>		<p>Vehicle Cradles for MC30/MC31/MC32</p>	<ul style="list-style-type: none"> <li>▶Holds MC30/MC31/MC32 Gun or Brick units.</li> <li>▶Front Facing - allows user to access screen and keyboard while cradled.</li> <li>▶Variable Mount - can be tilted and swiveled.</li> <li>▶Available in un-powered, cigarette lighter adapter powered, or hard-wired powered configurations.</li> <li>▶Mount ready via AMPS hole pattern</li> <li>▶Not compatible with MC33 units</li> </ul>	<p>Mount on vehicle using ProClip Pedestal or Forklift Mount - see ProClip website</p>
<p>MDMC3000 Available from MD Mobildata (3rd party) *</p>		<p>Vehicle/Fork Truck Cradle for MC30/MC31/MC32 Brick or Gun</p>	<ul style="list-style-type: none"> <li>▶Provides USB, RS232, and Power connectors</li> <li>▶USB and RS232 Connector on the backside enables connection of external GPRS or GPS Modules as well as a CANBus Connection for engine control.</li> <li>▶USB-Connector offers a USB-Client or USB-Host Connection</li> <li>▶Not compatible with MC33.</li> </ul>	








<p>MDMC3000 D-W Available from MD Mobildata (3rd party) *</p> <p><a href="http://www.mdmobildata.de">http://www.mdmobildata.de</a></p>		<p>MC30/MC31/MC32 Desktop/Wallmount Cradle</p>	<ul style="list-style-type: none"> <li>►Provides charging only</li> <li>►Cradle can be individually cascaded for multi-charger-use.</li> <li>►Can be also used for wall-mount, also in multi-charger option</li> <li>►Not compatible with MC33.</li> </ul>	
<p>0000-0481 (3rd party) *</p> <p><a href="http://www.multiplex.com/">http://www.multiplex.com/</a></p>		<p>MC30/MC31/MC32 vehicle cradle</p>	<ul style="list-style-type: none"> <li>►Cradle has USB and RS232 ports</li> <li>►The connection can be either an RS232 serial or a USB (client) connection.</li> <li>►Communication and charging cradle in cars, vans and fork lift trucks and can also be desk or wall mounted.</li> <li>►Serial port not compatible with Android versions of MC32.</li> <li>►Not compatible with MC33.</li> </ul>	
<p>SAC-MC33-4SCHG-01</p>		<p>MC32/MC33 4-Slot Battery Charger</p>	<ul style="list-style-type: none"> <li>►This cradle charges spare batteries only (1X/Standard or 2X/Extended size).</li> <li>►Supports charging of both MC33 and MC32 batteries.</li> <li>►Supports fast-charging of MC33 batteries: <ul style="list-style-type: none"> <li>- charges 1X battery from 0-90% in about 2 hours vs. 3 hours for standard charging rate.</li> <li>- charges 2X battery from 0-90% in about 3.5 hours vs. 5.5 hours for standard charging rate.</li> </ul> </li> <li>►Can be used standalone or up to four chargers can be installed on Multi-Slot Wall/Rack Mount Bracket (BRKT-SCRD-SMRK-01).</li> <li>►Not compatible with MC3000 or MC3100 series spare batteries.</li> </ul>	<p><u>To power single Charger</u></p> <ul style="list-style-type: none"> <li>►Power Supply (PWR-BGA12V50W0WWW and CBL-DC-388A1-01</li> <li>►AC Line Cord (23844-00-00R)</li> </ul> <p><u>To power two Chargers</u></p> <p>Power Supply (PWR-BGA12V50W0WWW), DC Cord (CBL-DC-388A1-01) , Two-Way Power Cable (25-122026-02R), and AC Line Cord (23844-00-00R)</p> <p><u>To power up to four Chargers</u></p> <p>Power Supply (PWR-BGA12V108W0WWW), Four-Way Power Cable (CBL-DC-380A1-01), and AC Line Cord (23844-00-00R)</p> <p><u>To power five Chargers</u></p> <p>Use MC33 20-Slot Battery Charger (SAC-MC33-20SCHG-01) instead.</p>
<p>SAC-MC33-20SCHG-01</p>		<p>MC32/MC33 20-Slot Battery Charger</p>	<ul style="list-style-type: none"> <li>►Charges MC33 or MC32 spare batteries (1X/Standard or 2X/Extended size).</li> <li>►Uses 5-Slot ShareCradle with five 4-Slot Battery Chargers (SAC-MC33-4SCHG-01) attached.</li> <li>►Does NOT support fast-charging of MC33 batteries. All battery types charged at standard rate: <ul style="list-style-type: none"> <li>- charges 1X battery from 0-90% in about 3 hours at standard charging rate.</li> <li>- charges 2X battery from 0-90% in about 5.5 hours at standard charging rate.</li> </ul> </li> <li>►Can be racked/mounted in a standard 19 inch rack system via the mounting accessory (BRKT-SCRD-SMRK-01).</li> <li>►Not compatible with MC3000 or MC3100 series spare batteries.</li> </ul>	<ul style="list-style-type: none"> <li>►DC Line Cord (CBL-DC-381A1-01) and Power Supply (PWR-BGA12V108W0WWW)</li> <li>►AC Line Cord (23844-00-00R)</li> </ul>


SAC7X00-4000CR		4-Slot Battery Charger	<ul style="list-style-type: none"> <li>▶This cradle charges spare batteries only (1X or 2X size).</li> <li>▶Provides IEEE1725 compliance.</li> <li>▶Same charger used by MC7X (does not support MC50)</li> <li>▶The shims are used with the MC7X</li> <li>▶Does not support charging of MC33 batteries.</li> </ul>	<ul style="list-style-type: none"> <li>▶Power Supply (PWR-BGA12V50W0WWW and CBL-DC-388A1-01)</li> <li>▶AC Line Cord (23844-00-00R)</li> <li>▶MC32 Battery Adapter (ADP-MC32-CUP0-04) for charging MC32 batteries.</li> </ul>
SAC-MC32-400US-01		4-Slot MC32 Battery Charger Kit	<ul style="list-style-type: none"> <li>▶To be discontinued 5/2019, now use SAC-MC33-4SCHG-01 and associated power supply and line cords - see PMB 10073.</li> <li>▶Charges MC32 batteries</li> <li>▶Includes SAC7X00-4000CR, ADP-MC32-CUP0-04, PWR-BGA12V50W0WWW, CBL-DC-388A1-01R and 23844-00-00R</li> <li>▶Provides IEEE1725 compliance.</li> <li>▶Energy Star Compliant</li> <li>▶Does not support charging of MC33 batteries.</li> </ul>	
SAC7X00-400CES		4-Slot Battery Charger Kit	<ul style="list-style-type: none"> <li>▶Includes SAC7X00-4000CR, PWR-BGA12V50W0WWW, CBL-DC-388A1-01R and 23844-00-00R</li> <li>▶Provides IEEE1725 compliance.</li> <li>▶Energy Star Compliant</li> <li>▶Does not support charging of MC33 batteries.</li> </ul>	<ul style="list-style-type: none"> <li>▶MC32 Battery Adapter (ADP-MC32-CUP0-04) for charging MC32 batteries.</li> </ul>
SAC-MC32-400INT-01		4-Slot MC32 Battery Charger Kit	<ul style="list-style-type: none"> <li>▶To be discontinued 5/2019, now use SAC-MC33-4SCHG-01 and associated power supply and line cords - see PMB 10073.</li> <li>▶Charges MC32 batteries</li> <li>▶Includes SAC7X00-4000CR, ADP-MC32-CUP0-04, PWR-BGA12V50W0WWW, CBL-DC-388A1-01R and 23844-00-00R</li> <li>▶Provides IEEE1725 compliance.</li> <li>▶Kit usually order by International customers</li> <li>▶Energy Star Compliant</li> <li>▶Does not support charging of MC33 batteries.</li> </ul>	<ul style="list-style-type: none"> <li>▶23844-00-00R</li> </ul>
SAC7X00-401CES		4-Slot Battery Charger Kit	<ul style="list-style-type: none"> <li>▶Includes SAC7X00-4000CR, PWR-BGA12V50W0WWW and CBL-DC-388A1-01R</li> <li>▶Provides IEEE1725 compliance.</li> <li>▶Kit usually order by International customers</li> <li>▶Energy Star Compliant</li> <li>▶Does not support charging of MC33 batteries.</li> </ul>	<ul style="list-style-type: none"> <li>▶23844-00-00R</li> <li>▶MC32 Battery Adapter (ADP-MC32-CUP0-04) for charging MC32 batteries.</li> </ul>
ADP-MC32-CUP0-01 (single pack)  ADP-MC32-CUP0-04 (four pack)		MC32 Battery Charger Adapter	<ul style="list-style-type: none"> <li>▶Allows MC32 batteries to be charged in 4-Slot Battery Charger (SAC7X00-4000CR) (order four pack) OR Single Slot Cradle (CRD3000-1001RR) (order single pack)</li> <li>▶Does not support charging of MC33 batteries.</li> </ul>	<ul style="list-style-type: none"> <li>4-Slot Battery Charger (SAC7X00-4000CR) OR Single Slot Cradle (CRD3000-1001RR)</li> </ul>

21-32665-45AR		UBC Adapter	<ul style="list-style-type: none"> <li>▶This device makes the charging of multiple batteries easy and cost effective. Simply snap the battery into the adapter and slide the adapter into the UBC charging station. The charging station holds up to four adapters.</li> <li>▶Charges standard and high capacity batteries</li> <li>▶Does not support charging of MC33 batteries.</li> </ul>	<ul style="list-style-type: none"> <li>▶KT32665-02R</li> <li>OR</li> <li>▶KT32665-03R</li> <li>OR</li> <li>▶UBC2000-I500DES</li> <li>▶MC32 Battery Adapter (ADP-MC32-CUP0-04) for charging MC32 batteries.</li> </ul>
UBC2000-I500DES		UBC Charging Station	<ul style="list-style-type: none"> <li>▶Quad bay charger. Holds four UBC adapter modules.</li> <li>▶Includes 50-16002-011R power cord and PWRS-14000-242R power supply</li> <li>▶Energy Star certified</li> <li>▶Does not support charging of MC33 batteries.</li> </ul>	<ul style="list-style-type: none"> <li>▶23844-00-00R</li> <li>▶1-4 UBC adapters (21-32665-45AR)</li> <li>▶MC32 Battery Adapter (ADP-MC32-CUP0-04) for charging MC32 batteries.</li> </ul>
UBC2000-45AR		UBC Charging Station Kit	<ul style="list-style-type: none"> <li>▶Quad bay charger. Holds four UBC adapter modules.</li> <li>▶Includes UBC2000-I500DES UBC Charging Station and four 21-32665-45AR UBC Adapters</li> <li>▶Does not support charging of MC33 batteries.</li> </ul>	<ul style="list-style-type: none"> <li>▶23844-00-00R</li> <li>▶MC32 Battery Adapter (ADP-MC32-CUP0-04) for charging MC32 batteries.</li> </ul>
VCA3000-01R		Auto Charge/Cigarette Lighter Adapter Cable	<ul style="list-style-type: none"> <li>▶12/24 volt DC input</li> <li>▶Not compatible with MC33.</li> </ul>	
25-70103-03R		Charge Only Cable Cup	<ul style="list-style-type: none"> <li>▶Not compatible with MC33.</li> </ul>	<ul style="list-style-type: none"> <li>▶Power Supply (PWR-BUA5V16W0WW),</li> <li>▶DC Line Cord (CBL-DC-383A1-01)</li> <li>▶AC Line Cord (50-16000-182R) for charging</li> </ul>
<b>Communication Cables</b>				
<b>Part Number</b>	<b>Picture</b>	<b>Description</b>	<b>Notes</b>	<b>Required Items</b>
CBL-MC33-USBCHG-01		MC33 USB Communication/Charging Cable	<ul style="list-style-type: none"> <li>▶Only compatible with MC33.</li> </ul>	<ul style="list-style-type: none"> <li><b>For charging:</b></li> <li>▶USB Power Supply (PWR-WUA5V12W0US)</li> </ul>
25-67868-03R		MC30/MC31/MC32 USB Client Communication/Charging Cable with Cup	<ul style="list-style-type: none"> <li>▶Not compatible with MC33.</li> </ul>	<ul style="list-style-type: none"> <li>▶Power Supply (PWR-BUA5V16W0WW),</li> <li>▶DC Line Cord (CBL-DC-383A1-01)</li> <li>▶AC Line Cord (50-16000-182R) for charging</li> </ul>
25-67866-03R		RS232/Serial Communication/Charging Cable with Cup	<ul style="list-style-type: none"> <li>▶Not compatible with Android versions of MC32.</li> <li>▶Not compatible with MC33.</li> </ul>	<ul style="list-style-type: none"> <li>▶Power Supply (PWR-BUA5V16W0WW),</li> <li>▶DC Line Cord (CBL-DC-383A1-01)</li> <li>▶AC Line Cord (50-16000-182R) for charging</li> </ul>
25-63852-01R		RS232/Serial Single-Slot cradle to ActiveSync PC/Host cable	<ul style="list-style-type: none"> <li>▶This is a spare cable. The CRD3000-1000 ships with this cable.</li> <li>▶Not compatible with Android versions of MC32.</li> <li>▶Not compatible with MC33.</li> </ul>	

25-124330-01R		MC33 USB Single-Slot Cradle to PC/Host cable	<ul style="list-style-type: none"> <li>►Used with the MC33 Single Slot Cradle (CRD-MC33-2SUCHG-01)</li> <li>►Micro USB connection on cradle end</li> </ul>	
25-68596-01R		USB Single-Slot cradle to ActiveSync PC/Host cable	<ul style="list-style-type: none"> <li>►Used with MC30/MC31/MC32 Single Slot Cradles.</li> <li>►Mini USB connection on cradle end</li> </ul>	
25-63856-01R		Modem Cable for Single-Slot Cradle	<ul style="list-style-type: none"> <li>►Needed to connect the MDM9000-100R (Modem Module) to the CRD3000-1000RR (Single Slot Cradle). Allows single slot cradle to be used as a modem cradle.</li> <li>►Not compatible with Android versions of MC32.</li> </ul>	<ul style="list-style-type: none"> <li>►MDM9000-100</li> <li>►CRD3000-1000RR</li> </ul>
PSAK-UCE (3rd party) *		USB Ethernet Adapter Kit	<ul style="list-style-type: none"> <li>►Connects to MC3x00 via Single Slot USB cradle. Acts as USB Peripheral device to MC3x00 (USB host)</li> <li>►Requires no separate power supply, has grounded wiring from both the USB and Ethernet ports, and operates on very low power draw directly from the USB connection.</li> <li>►Molded end caps enable the adapters to be aligned side by side or top to bottom, for efficient use of desktop space and organization of cables.</li> <li>►Kit includes PSA1U1E adapter and three USB cables for connecting to a variety of devices.</li> <li>►Requires software driver from <a href="http://www.portsmith.com">http://www.portsmith.com</a></li> </ul>	<p>CRD3000-1000RR and USB Mini A to Type B conversion cable 170573-000 (PortSmith cable included in kit)</p> <p>OR</p> <p>25-67868-03R and USB A Receptacle to Type-B Plug conversion cable. This will also require MC3x00 Control Panel applet software to force MC3x00 in USB Host mode.</p>
FAUSB01 (3rd party) *		USB A Female to USB A Female adapter	<ul style="list-style-type: none"> <li>►Allows the MC3000 to act as a USB host to connect to devices like USB flash drives, etc.</li> <li>►This adapter works with the MC3000 Cable Cup adapter.</li> </ul>	25-67868-03R OR 25-67869-03R
GXQU-06 (3rd party) *		JDI GoldX QuickConnect 5-in-1 USB Cable Kit (6 ft.)	<ul style="list-style-type: none"> <li>►Allows the MC3000 to act as a USB host to connect to devices like USB flash drives, etc.</li> <li>►This cable works with the MC3000 Single Slot cradle</li> <li>►Use a mini A connector on one end and an A female connector on the other end.</li> </ul>	CRD3000-1000RR
RDUYS08220007		USB mini-A to USB A Female adapter	<ul style="list-style-type: none"> <li>►Allows the MC30xx to act as a USB host to connect to devices like USB flash drives/memory sticks, mice, etc.</li> <li>►This adapter works with the MC3000 Single Slot Cradle.</li> </ul>	
190087-000 (3rd party) *		USB Adapter Cable: type-A receptacle to mini-B plug	<ul style="list-style-type: none"> <li>►Allows the MC3000 USB Client Communication/Charging Cable with Cup to be connected to USB client peripherals like PortSmith's USB Ethernet Adapter.</li> <li>►Can also be used to connect to other peripherals with a mini USB-B connector.</li> </ul>	




170373-000 (3rd party) *  <a href="http://www.portsmith.com">http://www.portsmith.com</a>		USB Cable: mini-A plug to mini-B plug	<ul style="list-style-type: none"> <li>Allows the MC3000 Single Slot Cradle to be connected to USB client peripherals like PortSmith's USB Ethernet Adapter.</li> <li>Can also be used to connect to other peripherals with a mini USB-B connector.</li> </ul>	
P1031365-058		Cable Cup Adapter to QLn or ZQ6 Series Printers	<ul style="list-style-type: none"> <li>50" coiled cable</li> <li>Not compatible with Android versions of MC32.</li> <li>Not compatible with MC33.</li> </ul>	
P1031365-060		Cable Cup Adapter to QLn or ZQ6 Series Printers	<ul style="list-style-type: none"> <li>50" coiled cable</li> <li>Uses non-standard cable pin-out to MC3X00 - DSR will always be high.</li> <li>Not compatible with Android versions of MC32.</li> <li>Not compatible with MC33.</li> </ul>	
25-91513-01R		Cable Cup Adapter to QL Series Printers	<ul style="list-style-type: none"> <li>Not compatible with Android versions of MC32.</li> <li>Not compatible with MC33.</li> </ul>	
25-91512-01R		Cable Cup Adapter to O'Neil Printers	<ul style="list-style-type: none"> <li>Not compatible with Android versions of MC32.</li> <li>Not compatible with MC33.</li> </ul>	
CBL-8800-100-DEXR		DEX Cable for MSR3000	<ul style="list-style-type: none"> <li>Not compatible with Android versions of MC32.</li> <li>Not compatible with MC33.</li> </ul>	MSR3000-100R
CBL-8800-100-ON1R		O'Neil Printer Cable for MSR3000	<ul style="list-style-type: none"> <li>Not compatible with Android versions of MC32.</li> <li>Not compatible with MC33.</li> </ul>	MSR3000-100R
CBL-8800-100-PAXR		Paxar Printer Cable for MSR3000	<ul style="list-style-type: none"> <li>Not compatible with Android versions of MC32.</li> <li>Not compatible with MC33.</li> </ul>	MSR3000-100R






CBL-8800-100-ZEBR		Zebra QL Series Printer Cable for MSR3000	<ul style="list-style-type: none"> <li>Connects to QL series Zebra Printers</li> <li>Not compatible with Android versions of MC32.</li> <li>Not compatible with MC33.</li> </ul>	MSR3000-100R
<b>Snap-On Accessories</b>				
<b>Part Number</b>	<b>Picture</b>	<b>Description</b>	<b>Notes</b>	<b>Required Items</b>
<b>Misc</b>				
<b>Part Number</b>	<b>Picture</b>	<b>Description</b>	<b>Notes</b>	<b>Required Items</b>
SG-MC33-RDHLST-01		MC33 Rigid Holster	<ul style="list-style-type: none"> <li>This carrying case secures the device to a belt.</li> <li>Only compatible with MC33, except MC33 RFID units.</li> <li>Not compatible with devices having Rubber Boot installed.</li> </ul>	
8710-050005-01R		MC30/MC31/MC32 Rigid Holster	<ul style="list-style-type: none"> <li>This carrying case secures the device to a belt.</li> <li>Not compatible with devices having Rubber Boot installed.</li> <li>Not compatible with MC33.</li> </ul>	
SG-MC3X-SHLSTB-01		Fabric Holster for Brick/Straight-Shooter or Rotating Head configurations	<ul style="list-style-type: none"> <li>This carrying case secures the MC3x00 to a belt (using belt clip) or can be worn cross-body (using included strap).</li> <li>Compatible with all MC3X series Brick/Straight Shooter or Rotating Head units, including MC33.</li> <li>Devices with Rubber Boot installed will fit into Holster. The fit will be tight though.</li> <li>Uses modified strap to secure device in holster vs. 11-69293-01R.</li> </ul>	
SG-MC3021212-01R		Fabric Holster for Gun configuration	<ul style="list-style-type: none"> <li>Includes modification with a softer belt loop and stronger button snap to avoid the button from snapping open when the MC3x00 is inserted into the holster.</li> <li>Devices with Rubber Boot (11-72959-04R) will fit into Holster. The fit will be tight though.</li> <li>Compatible with all MC3X series, including MC33.</li> <li>MC33 RFID units must be inserted into cradle with bottom of device inserted first.</li> </ul>	
AA1036DW (3rd party) * <a href="http://www.ultimacase.com">http://www.ultimacase.com</a>		MC3XXX-G (Gun) Forklift Holster 	<ul style="list-style-type: none"> <li>Includes cable ties for mounting holster to forklift</li> <li>Does not provide device charging</li> </ul>	






<p>T5963DWSP (3rd party) *</p> <p><a href="http://www.ultimacase.com">http://www.ultimacase.com</a></p>		<p>MC30/MC31/MC32 SoftTouch Case with D-swivel for Straight Shooter or Turret Head configuration</p> 	<ul style="list-style-type: none"> <li>▶Direct access to side triggers, and belt loop with low profile D-swivel for quick and secure attachment to waist belt.</li> <li>▶Raised edges for display protection against short drops.</li> <li>▶See-thru polyurethane protects keypad.</li> <li>▶Cutouts on sides for access to triggers.</li> <li>▶Elastic loop for keeping stylus</li> <li>▶Not compatible with MC33.</li> </ul>	
<p>O4925DWSP0S2 (3rd party) *</p> <p><a href="http://www.ultimacase.com">http://www.ultimacase.com</a></p>		<p>Replacement Swivel Belt Clips for holsters</p> 		
<p>11-08062-02R</p>		<p>Belt for holster</p>	<ul style="list-style-type: none"> <li>▶Belt is 2 inches wide</li> <li>▶Extends to 48 inches</li> <li>▶Has improved buckle and softer belt material</li> </ul>	
<p>V6198DW (3rd party) *</p> <p><a href="http://www.ultimacase.com">http://www.ultimacase.com</a></p>		<p>Belt Extender</p>	<ul style="list-style-type: none"> <li>▶Used to extend the holster belt (11-08062-02R) an additional 10 inches</li> </ul>	
<p>SG-MC33-HDSTPG-01</p>		<p>Replacement MC33 Gun Handstrap</p>	<ul style="list-style-type: none"> <li>▶This is the same strap that ships with the MC33 Gun units.</li> <li>▶Only compatible with MC33.</li> </ul>	














<p>SG-MC3123242-01R (single strap)</p>		<p>Replacement MC31/MC32 Gun Handstrap</p>	<ul style="list-style-type: none"> <li>▶This is the same strap that ships with the MC31/MC32 Gun units.</li> <li>▶Includes UHF Gen2 tag for asset tracking.</li> <li>▶Not compatible with MC33.</li> </ul>	
<p>SG-MC32-HDSTG-01 (pack of 3)</p>		<p>Replacement MC31/MC32/MC33 Gun Handstraps</p>	<ul style="list-style-type: none"> <li>▶This is an alternative lower cost hand strap for MC31/MC32/MC33 Gun units.</li> <li>▶Lower profile strap does not include UHF RFID tag for asset tracking.</li> </ul>	
<p>SG-MC3123342-01R (pack of 5)</p>		<p>MC31/MC32/MC33 Gun Handstrap</p>	<ul style="list-style-type: none"> <li>▶This is an alternative strap for the MC31/MC32/MC33 Gun for customers that don't want a full handstrap that connects from the battery door or bottom of device to the gun handle.</li> <li>▶D ring provides convenient pull point to remove battery cover on MC31 units.</li> </ul>	
<p>SG-MC33-HDSTPB-01</p>		<p>Replacement MC33 Brick or Turret Head Handstrap</p>	<ul style="list-style-type: none"> <li>▶This is the same strap that ships with the MC3 Brick (straight shooter) or Turret Head units.</li> <li>▶Includes loop for storing optional stylus.</li> <li>▶Only compatible with MC33.</li> </ul>	




<p>MC3123244-01R</p>		<p>Replacement MC31/MC32 Brick or Turret Head Handstrap</p>	<ul style="list-style-type: none"> <li>▶This is the same strap that ships with the MC31/MC32 Brick (straight shooter) or Turret Head units.</li> <li>▶Includes UHF Gen2 RFID tag for asset tracking.</li> <li>▶Includes loop for storing optional stylus</li> <li>▶Not compatible with MC33.</li> </ul>	
<p>SG-MC33-LNYDB-01</p>		<p>Lanyard for Brick/Straight-Shooter or Turret Head units</p>	<ul style="list-style-type: none"> <li>▶Allows MC32 or MC33 Brick/Straight-Shooter or Turret Head units to be attached to a retractable lanyard.</li> <li>▶Lanyard can be worn cross-body using included strap or strap can be removed and lanyard can be attached to belt.</li> <li>▶Standard handstrap must be removed to allow lanyard to be attached to MC3X unit.</li> <li>▶When using as belt mounted lanyard, can be used with Belt for Holster (11-08062-02R)</li> </ul>	




SG-MC33-RBTS-01		Rubber Boot for MC33 Brick/Straight-Shooter units	<ul style="list-style-type: none"> <li>•Works with Imager configuration brick/straight-shooter units</li> <li>•Only compatible with MC33.</li> <li>•Does not increase drop spec of device. Designed to protect the device from the everyday nicks and dings.</li> <li>•Compatible with fabric holsters.</li> <li>•Not compatible with Forklift Holder</li> <li>•Boot must be removed before inserting into cradles.</li> </ul>	
11-70899-04R		Rubber Boot for MC30/MC31/MC32 Brick/Straight-Shooter units	<ul style="list-style-type: none"> <li>•Works with Imager configuration brick/straight-shooter units</li> <li>•Not compatible with MC33.</li> <li>•Compatible with fabric holsters.</li> <li>•Not compatible with Forklift Holder</li> <li>•Boot must be removed before inserting into cradles.</li> </ul>	
SG-MC33-RBTRD-01		Boot for MC33 Turret Head Scanner	<ul style="list-style-type: none"> <li>•Works with Turret Head Scanner configuration units.</li> <li>•Includes Boot for unit.</li> <li>•Only compatible with MC33.</li> <li>•Does not increase drop spec of device. Designed to protect the device from the everyday nicks and dings.</li> <li>•Compatible with fabric holsters.</li> <li>•Not compatible with Forklift Holder</li> <li>•Boot must be removed before inserting into cradles.</li> </ul>	Typically ordered with Cup for Turret Head Scanner (SG- MC33-RBTRT-01)
SG-MC33-RBTRT-01		Cup for MC33 Turret Head Scanner	<ul style="list-style-type: none"> <li>•Only compatible with MC33.</li> <li>•Does not increase drop spec of device. Designed to protect the device from the everyday nicks and dings.</li> </ul>	Typically ordered with Boot for Turret Head Scanner (SG- MC33-RBTRD-01)
BOOTSCANTURRETR		Boot for MC30/MC31/MC32 Turret Head Scanner	<ul style="list-style-type: none"> <li>•Works with Turret Head Scanner configuration units.</li> <li>•Includes Boot for unit and Boot for Turret Head scanner.</li> <li>•Not compatible with MC33.</li> <li>•Compatible with fabric holsters.</li> <li>•Not compatible with Forklift Holder</li> <li>•Boot must be removed before inserting into cradles.</li> </ul>	

11-72096-04R		Boot Cup for MC30/MC31/MC32 Turret Head Scanner	<ul style="list-style-type: none"> <li>Includes only the turret head boot that is included with BOOTSCANTURRETR.</li> <li>Not compatible with MC33.</li> </ul>	
SG-MC33-RBTG-01		Rubber Boot for MC33 Gun	<ul style="list-style-type: none"> <li>Works with both Laser and Imager gun units</li> <li>Devices with Boot will also fit into Fabric Gun Holster (SG-MC3021212-01R). The fit will be tight though.</li> <li>Only compatible with MC33, except MC33 RFID units..</li> <li>Does not increase drop spec of device. Designed to protect the device from the everyday nicks and dings.</li> <li>Compatible with fabric holsters.</li> <li>Not compatible with Forklift Holder</li> <li>Boot must be removed before inserting into cradles.</li> </ul>	
11-72959-04R		Rubber Boot for MC30/MC31/MC32 Gun	<ul style="list-style-type: none"> <li>Works with both Laser and Imager gun units</li> <li>Devices with Boot will also fit into Fabric Gun Holster (SG-MC3021212-01R). The fit will be tight though.</li> <li>Not compatible with MC33.</li> <li>Compatible with fabric holsters.</li> <li>Not compatible with Forklift Holder</li> <li>Boot must be removed before inserting into cradles.</li> </ul>	
SG-MC33-RBTG-02		Rubber Boot for MC33 RFID unit	<ul style="list-style-type: none"> <li>Only compatible with MC33 RFID units.</li> <li>Includes holder for optional stylus (SG-TC7X-STYLUS-03), which is not included, and tether point for stylus tether.</li> <li>Does not increase drop spec of device. Designed to protect the device from the everyday nicks and dings.</li> <li>Devices with Boot will also fit into Fabric Gun Holster (SG-MC3021212-01R) - bottom of MC33 RFID device will insert into holster. The fit will be tight though.</li> <li>Not compatible with Forklift Holder</li> <li>Boot must be removed before inserting into cradles.</li> </ul>	
SG-MC33-RBTG-03		Half Rubber Boot for MC33 RFID unit	<ul style="list-style-type: none"> <li>Only compatible with MC33 RFID units.</li> <li>Includes holder for optional stylus (SG-TC7X-STYLUS-03), which is not included, and tether point for stylus tether.</li> <li>Does not increase drop spec of device. Designed to protect the device from the everyday nicks and dings.</li> <li>Devices with Boot will also fit into Fabric Gun Holster (SG-MC3021212-01R) - bottom of MC33 RFID device will insert into holster. The fit will be tight though.</li> <li>Not compatible with Forklift Holder</li> <li>Boot covers top half of device allowing easy insertion into cradles.</li> </ul>	

<p>T5977DW (3rd party) *</p> <p><a href="http://www.ultimacase.com">http://www.ultimacase.com</a></p>		<p>Heated case for MC30/MC31/MC32 Brick</p>	<ul style="list-style-type: none"> <li>•For use in environments that are colder than the MC30xx's operating specs.</li> <li>•Ballistic nylon OP Case is designed with Thinsulate padding for minimizing heat loss</li> <li>•Two pockets are sewn inside the case for storing Heat Packs that keep the unit warm</li> <li>•Heat Packs have temperature range of 104F to 156F (40C to 69C) and last up to 7 hours</li> <li>•Top flap with snaps allows quick and easy insertion or removal of the unit</li> <li>•Elastic hand strap is sewn on back for holding the unit in palm during use</li> <li>•2 D-rings allow attachment to an optional shoulder strap</li> </ul>	<p>Requires heat packs which are also available on web site.</p>
<p>(3rd party) *</p> <p><a href="http://www.ultimacase.com">http://www.ultimacase.com</a></p>	<p>Agora Leather website</p>	<p>Additional holsters for MC3000 series</p>		
<p>0000-0543 (3rd party) *</p> <p><a href="http://www.multiplex.com/">http://www.multiplex.com/</a></p>		<p>Hip holster with belt for MC3X Brick/Straight-Shooter units</p>	<ul style="list-style-type: none"> <li>•Left-hand/right-hand interchangeable</li> <li>•The holster and belt provide protection and hands free mobility to sensitive equipment</li> </ul>	
<p>0000-0540 (3rd party) *</p> <p><a href="http://www.multiplex.com/">http://www.multiplex.com/</a></p>		<p>MC30/MC31/MC32 Turret Head Configuration Holster, display exposed with shoulder strap</p>	<ul style="list-style-type: none"> <li>•Display exposed for touch screen ease.</li> <li>•Includes shoulder strap.</li> <li>•Not compatible with MC33.</li> </ul>	
<p>(3rd party) *</p> <p><a href="http://logisterra.com/products/symbol/symbol.html">http://logisterra.com/products/symbol/symbol.html</a></p>	<p>Logisterra website</p>	<p>Additional Holsters for MC3000 series</p>		
<p>SG-TC7X-STYLUS-03 (pack of 3)</p>		<p>MC33 Stylus Kit with Tether</p>	<ul style="list-style-type: none"> <li>•Only compatible with MC33</li> <li>•Includes fine-pitch, capacitive Stylus (SG-TC7X-STYLUS1-03) and coiled tether (KT-TC7X-TETHER1-03)</li> <li>•Conductive Carbon-filled plastic material w/ 5mm tip.</li> <li>•Length of stylus is 3.5".</li> <li>•Rigid plastic stylus is optimized for enterprise durability.</li> <li>•Clip &amp; tether point to reduce loss. Tether to Handstrap</li> <li>•When not being used stylus can be stored in loop on Handstrap or in the optional Holster</li> </ul>	








<p>SG-TC7X-STYEX1-3 (pack of 3)</p>		<p>MC33 Extended Length Stylus</p>	<ul style="list-style-type: none"> <li>▶Only compatible with MC33</li> <li>▶Conductive Carbon-filled plastic material w/ 5mm tip</li> <li>▶Rigid plastic stylus is optimized for enterprise durability.</li> <li>▶Clip &amp; tether point to reduce loss.</li> <li>▶When not being used stylus can be stored in optional Holster</li> <li>▶Use with optional Tether (SG-ET5X-SLTETR-01)</li> <li>▶To be discontinued 2/2019 - see PMB 10057</li> </ul>	
<p>KT-MC9X3X-STLSG-05 (pack of 5)</p> <p>KT-MC9X3X-STLSG-10 (pack of 10)</p> <p>KT-MC9X3X-STLSG-50 (pack of 50)</p>		<p>Spare Stylus for MC30/MC31/MC32 Gun</p>	<ul style="list-style-type: none"> <li>▶This is the standard stylus that ships with the unit</li> <li>▶Not compatible with MC33.</li> </ul>	
<p>11-43912-03R (pack of 3)</p> <p>11-43912-50R (pack of 50)</p>		<p>Spare Tethered Stylus for MC30/MC31/MC32 Brick</p>	<p>This is the standard stylus that ships with the unit. Includes 11-42794-XX Stylus and 11-42722-XX Tethers</p> <ul style="list-style-type: none"> <li>▶Not compatible with MC33.</li> </ul>	
<p>11-42794-03R (pack of 3)</p> <p>11-42794-50R (pack of 50) - Discontinued 12/2013</p>		<p>Tetherable Stylus for MC30/MC31/MC32 Brick</p>	<ul style="list-style-type: none"> <li>▶Not compatible with MC33.</li> </ul>	
<p>SG-ET5X-SLTETR-01</p>		<p>Coiled Tether for Stylus</p>	<ul style="list-style-type: none"> <li>▶Typically used with MC33 Stylus</li> </ul>	
<p>KT-73440-01R</p>		<p>Non-Elastic Tethers (pack of 3)</p>	<ul style="list-style-type: none"> <li>▶Typically used with MC30/MC31/MC32 Stylus</li> </ul>	
<p>11-42722-03R (pack of 3)</p> <p>11-42722-50R (pack of 50)</p>		<p>Elastic Tethers</p>	<ul style="list-style-type: none"> <li>▶Typically used with MC30/MC31/MC32 Stylus</li> </ul>	







HS2100-OTH		HS2100 Rugged Wired Headset (Over the Head headband)	<ul style="list-style-type: none"> <li>•Built to handle the everyday inevitable drops</li> <li>•Dustproof, sprayproof and waterproof</li> <li>•Ready for the freezer and outdoor subzero temperatures</li> <li>•Feather-light for extraordinary comfort</li> <li>•Noise cancellation for a superior voice experience in the noisiest environments</li> <li>•Detachable swivel boom minimizes costs.</li> <li>•Swivelling boom mutes microphone allowing uses to prevent voice pick applications from recognizing non-voice pick conversations.</li> <li>•User-replaceable pads and windscreens maximize comfort and hygiene.</li> <li>•Not compatible with MC31/MC33 RFID units which do not have a headset jack.</li> </ul>	<p>For MC31/MC32/MC33: Quick Disconnect Headset cable (CBL-HS2100-QDC1-01) AND MC31/MC32 to Quick Disconnect Adapter Cable (25-124411-02R)</p> <p>For MC3000: Quick Disconnect Headset cable (CBL-HS2100-QDC1-01) AND MC3000 to Quick Disconnect Adapter Cable (25-124387-02R)</p>
HS2100-BTN-L		HS2100 Rugged Wired Headset (Behind the Neck Left headband)	<ul style="list-style-type: none"> <li>•Built to handle the everyday inevitable drops</li> <li>•Dustproof, sprayproof and waterproof</li> <li>•Ready for the freezer and outdoor subzero temperatures</li> <li>•Feather-light for extraordinary comfort</li> <li>•Noise cancellation for a superior voice experience in the noisiest environments</li> <li>•Detachable swivel boom minimizes costs.</li> <li>•Swivelling boom mutes microphone allowing uses to prevent voice pick applications from recognizing non-voice pick conversations.</li> <li>•User-replaceable pads and windscreens maximize comfort and hygiene.</li> <li>•Not compatible with MC31/MC33 RFID units which do not have a headset jack.</li> </ul>	<p>For MC31/MC32/MC33: Quick Disconnect Headset cable (CBL-HS2100-QDC1-01) AND MC31/MC32 to Quick Disconnect Adapter Cable (25-124411-02R)</p> <p>For MC3000: Quick Disconnect Headset cable (CBL-HS2100-QDC1-01) AND MC3000 to Quick Disconnect Adapter Cable (25-124387-02R)</p>
RCH51		RCH51 Rugged Cabled Headset	<ul style="list-style-type: none"> <li>•Improved to withstand chemicals in certain hair gels</li> <li>•Noise cancelling microphone filters ambient noise inches away</li> <li>•Extremely rugged strain relief features ensure cable bend tolerance, even at -30C</li> <li>•IP67 sealing throughout the headset protects sensitive components from moisture and dust</li> <li>•High-strength plastics survive 6' drop at -30C &amp; 500 tumbles</li> <li>•Weight: 4 oz.</li> <li>•See RCH50/RCH51 Accessories Document for additional accessories.</li> <li>•Not compatible with MC31/MC33 RFID units which do not have a headset jack.</li> </ul>	<p>For MC30XX series: Headset Adapter Cable (25-124387-02R)</p> <p>For MC31/MC32/MC33 series: Headset Adapter Cable (25-124411-02R)</p>








<p>3PTY-VXI-VR12 (Zebra orderable SKU)</p> <p><a href="http://www.vxicorp.com">http://www.vxicorp.com</a></p>		<p>VXi VR12 Wired Noise Cancelling Headset</p> 	<ul style="list-style-type: none"> <li>•To be discontinued 10/2018, now use HS2100 series - PMB 10005</li> <li>•Audio accuracy for voice picking and other speech recognition applications.</li> <li>•High quality durability stands up to all-day, every-day use.</li> <li>•Lightweight design is easy and comfortable to wear all day.</li> <li>•Compatible with most major wearable computers and devices used in voice-picking environments.</li> <li>•G type (GN Netcom) Quick Disconnect.</li> <li>•Convertible design gives choice of over-the-head and behind-the-neck wearing styles.</li> <li>•Not compatible with MC31/MC33 RFID units which do not have a headset jack.</li> </ul>	<p>For MC30XX series: Headset Adapter Cable (25-124387-02R) For MC31/MC32/MC33 series: Headset Adapter Cable (25-124411-02R)</p>
<p>HS3100-OTH</p>		<p>HS3100 Rugged Bluetooth Headset (Over the Head headband)</p>	<ul style="list-style-type: none"> <li>•HD Voice, also known as Wide Band Audio, brings incredible audio clarity</li> <li>•Built to handle the everyday inevitable drops</li> <li>•Dustproof, sprayproof and waterproof</li> <li>•Ready for the freezer and outdoor subzero temperatures</li> <li>•Feather-light for extraordinary comfort</li> <li>•Noise cancellation for a superior voice experience in the noisiest environments</li> <li>•Swap batteries on the fly — without losing the Bluetooth connection</li> <li>•Split-second tap-to-pair simplicity using NFC.</li> <li>•Detachable swivel boom minimizes costs.</li> <li>•Swivelling boom mutes microphone allowing uses to prevent voice pick applications from recognizing non-voice pick conversations.</li> <li>•User-replaceable pads and windscreens maximize comfort and hygiene</li> <li>•15 hours of battery power</li> <li>•Compatible with MC33 or MC32 WEC7 units only. Not compatible with MC32 Android Jellybean units.</li> </ul>	<p>See HS2100/HS3100 Accessories Document for headset accessories</p>











<p>HS3100-BTN-L</p>		<p>HS3100 Rugged Bluetooth Headset (Behind the Neck Headband Left)</p>	<ul style="list-style-type: none"> <li>•HD Voice, also known as Wide Band Audio, brings incredible audio clarity</li> <li>•Built to handle the everyday inevitable drops</li> <li>•Dustproof, sprayproof and waterproof</li> <li>•Ready for the freezer and outdoor subzero temperatures</li> <li>•Feather-light for extraordinary comfort</li> <li>•Noise cancellation for a superior voice experience in the noisiest environments</li> <li>•Swap batteries on the fly – without losing the Bluetooth connection</li> <li>•Split-second tap-to-pair simplicity using NFC.</li> <li>•Detachable swivel boom minimizes costs.</li> <li>•Swivelling boom mutes microphone allowing uses to prevent voice pick applications from recognizing non-voice pick conversations.</li> <li>•User-replaceable pads and windscreens maximize comfort and hygiene</li> <li>•15 hours of battery power</li> <li>•Compatible with MC33 or MC32 WEC7 units only. Not compatible with MC32 Android Jellybean units.</li> </ul>	<p>See HS2100/HS3100 Accessories Document for headset accessories</p>
<p>3PTY-VXI-B350XT (Zebra orderable SKU)</p> <p><a href="http://www.vxicorp.com">http://www.vxicorp.com</a></p>		<p>VXi BlueParrott Bluetooth Headset for voice directed applications</p> 	<ul style="list-style-type: none"> <li>•To be discontinued 10/2018, now use HS3100 series - PMB 10005</li> <li>•Used to enable Voice Directed Picking (VDP) or Speech Applications in warehouse environments when the use of a wireless headset is desired</li> <li>•<b>Not</b> intended to support peer-to-peer communications (PTT) or VoIP calls.</li> <li>•Provides 24 hours talk time.</li> <li>•Works with StoneStreet Bluetooth stack. Will not function with Microsoft BT stack or voice applications that depend on the Microsoft BT stack.</li> <li>•Allows the use of other BT devices (i.e. RS507 scanner or mobile printer)</li> <li>•Compatible with MC33 or MC32 WEC7 units only. Not compatible with MC32 Android Jellybean units.</li> <li>•Zebra Compatible certification for VDP application use with MC32.</li> </ul>	<ul style="list-style-type: none"> <li>•MC32 CE7 devices may require Bluetooth Wideband Speech CAB file from support site to enable StoneStreet BT stack wideband (16 KHz) audio support.</li> </ul>
<p>3PTY-VXI-B250XTP (Zebra orderable SKU)</p> <p><a href="http://www.vxicorp.com">http://www.vxicorp.com</a></p>		<p>VXi BlueParrott Bluetooth Headset for voice directed applications</p> 	<ul style="list-style-type: none"> <li>•To be discontinued 10/2018, now use HS3100 series - PMB 10005</li> <li>•Used to enable Voice Directed Picking (VDP) or Speech Applications in warehouse environments when the use of a wireless headset is desired</li> <li>•<b>Not</b> intended to support peer-to-peer communications (PTT) or VoIP calls.</li> <li>•Provides 20 hours talk time.</li> <li>•Works with StoneStreet Bluetooth stack. Will not function with Microsoft BT stack or voice applications that depend on the Microsoft BT stack.</li> <li>•Allows the use of other BT devices (i.e. RS507 scanner or mobile printer)</li> <li>•Compatible with MC33 or MC32 WEC7 units only. Not compatible with MC32 Android Jellybean units.</li> </ul>	<ul style="list-style-type: none"> <li>•MC32 CE7 devices may require Bluetooth Wideband Speech CAB file from support site to enable StoneStreet BT stack wideband (16 KHz) audio support.</li> </ul>

<p>3PTY-VXI-EXPWAYII (Zebra orderable SKU)</p> <p><a href="http://www.vxicorp.com">http://www.vxicorp.com</a></p>		<p>VXi BlueParrott Bluetooth Headset for voice directed applications</p> 	<ul style="list-style-type: none"> <li>▶To be discontinued 10/2018, now use HS3100 series - PMB 10005</li> <li>▶Used to enable Voice Directed Picking (VDP) or Speech Applications in warehouse environments when the use of a wireless headset is desired</li> <li>▶<b>Not</b> intended to support peer-to-peer communications (PTT) or VoIP calls.</li> <li>▶Provides 8 hours talk time.</li> <li>▶Works with StoneStreet Bluetooth stack. Will not function with Microsoft BT stack or voice applications that depend on the Microsoft BT stack.</li> <li>▶Allows the use of other BT devices (i.e. RS507 scanner or mobile printer)</li> <li>▶Compatible with MC33 or MC32 WEC7 units only. Not compatible with MC32 Android Jellybean units.</li> <li>▶Zebra Compatible certification for VDP application use with MC92, VC70, WT41 and MC32.</li> </ul>	<ul style="list-style-type: none"> <li>▶MC32 CE7 devices may require Bluetooth Wideband Speech CAB file from support site to enable StoneStreet BT stack wideband (16 Khz) audio support.</li> </ul>
<p>CBL-HS2100-QDC1-01</p>		<p>HS2100 Quick Disconnect Cable</p>	<ul style="list-style-type: none"> <li>▶For use when connecting HS2100 to devices using standard Quick Disconnect jack.</li> </ul>	
<p>25-124389-01R</p>		<p>MC31/MC32/MC33 Headset Adapter Cable, bare wire</p>	<ul style="list-style-type: none"> <li>▶Cable has right angle connector and locking screw into the MC31/32/33's audio jack.</li> <li>▶Bare wire end connector allows other manufacturers to build their own proprietary connectors on the opposite end for connections to other headsets.</li> <li>▶Not compatible with MC31/MC33 RFID units which do not have a headset jack.</li> </ul>	
<p>25-124411-03R</p>		<p>MC31/MC32/MC33 Headset Adapter Cable, HS2100 / RCH50/ VXI connector</p>	<ul style="list-style-type: none"> <li>▶Cable has right angle connector and locking screw into the MC31/32/33's audio jack.</li> <li>▶Connects HS2100, RCH50, VXI, Voxware, and Eartec headsets</li> <li>▶Updated cable minimizes cross talk and intermittency issues.</li> <li>▶Not compatible with MC31/MC33 RFID units which do not have a headset jack.</li> </ul>	
<p>25-124387-02R</p>		<p>MC30 HS2100/ RCH50/ RCH51 Headset Adapter Cable</p>	<ul style="list-style-type: none"> <li>▶Connects HS2100/RCH50/RCH51 headset to devices with standard 3-pole 2.5mm barrel jack connector.</li> <li>▶Updated cable minimizes cross talk and intermittency issues.</li> </ul>	
<p>MISC-MC33-SCRN-01 (pack of 5)</p>		<p>MC33 Tempered Glass Screen Protector (pack of 5)</p>	<ul style="list-style-type: none"> <li>▶Tempered glass</li> <li>▶Includes alcohol wipes, cleaning cloth, and tools needed for screen protector installation.</li> </ul>	

<p>Additional Screen Protectors (3rd party) *</p> <p><a href="http://www.nushield.com">http://www.nushield.com</a></p>		<p>Additional Screen Protectors</p>	<ul style="list-style-type: none"> <li>•NuShield AG™ - works well indoors under bright lights to minimize glare.</li> <li>•NuShield AM™ - antimicrobial film is an antiglare film designed for hospitals, public kiosks, restaurants and POS terminals where transmission of disease is a primary concern.</li> <li>•NuShield DayVue™ - antireflective film is the best choice for displays that are being used outdoors.</li> </ul>	
<b>Power Cords/Power Supplies</b>				
Part Number	Picture	Description	Notes	Required Items
CBL-DC-388A1-01		DC Power Cord	<ul style="list-style-type: none"> <li>•Used along with Power Supply PWR-BGA12V50W0WW to power Single Slot Cradle and SACX000 4-Slot Battery Charger.</li> <li>•Cable length is 1.8 meters</li> </ul>	
25-122026-02R		2-Way Power Cable	<ul style="list-style-type: none"> <li>•Used to power two MC33 Four Slot Battery Chargers (SAC-MC33-4SCHG-01) from one power supply (PWR-BGA12V50W0WW / PWRS-14000-148C).</li> <li>•Has a longer barrel jack and retention feature to ensure a good connection to the cradle.</li> </ul>	
PWR-BGA12V50W0WW		Power Supply	<ul style="list-style-type: none"> <li>•Used to power Single Slot Cradles, MC32/MC33 4-Slot Battery Charger, and SACX000 4-Slot Battery Charger.</li> <li>•100-240 VAC, 12V, 4.16A, 50W</li> <li>•Provides US DOE Level VI compliance for power efficiency.</li> <li>•Replaces PWRS-14000-148R</li> </ul>	DC Line Cord (CBL-DC-388A1-01) and AC Line Cord (23844-00-00R)
KIT-PWR-12V50W		Power Supply Kit	<ul style="list-style-type: none"> <li>•Includes Power Supply (PWR-BGA12V50W0WW) and DC Line Cord (CBL-DC-388A1-01)</li> </ul>	AC Line Cord (23844-00-00R)
CBL-DC-383A1-01		DC Line Cord	<ul style="list-style-type: none"> <li>•Used to power Snap-On USB/Charge Cable with Power Supply PWR-BUA5V16W0WW</li> <li>•Cable length is 6 ft.</li> </ul>	
PWR-BUA5V16W0WW		Power Supply	<ul style="list-style-type: none"> <li>•Used with Communication/Charge Cable Cups</li> <li>•100-240VAC, 5.4V, 3A, 16W</li> <li>•Meets US DOE Level VI efficiency standard</li> <li>•Replaces PWRS-14000-249R</li> </ul>	DC Line Cord (CBL-DC-383A1-01) and AC Line Cord (50-16000-182R)

CBL-DC-381A1-01		DC Power Cord	<ul style="list-style-type: none"> <li>Used with Power Supply PWR-BGA12V108W0WW to power MC33 5-Slot Multi-Slot ShareCradles and MC32/MC33 20-Slot Spare Battery Charger.</li> <li>This cable does not include the black extension release latch which is not required when used on Multi-Slot ShareCradles.</li> </ul>	
CBL-DC-382A1-01		DC Power Cord	<ul style="list-style-type: none"> <li>Used with Power Supply PWR-BGA12V108W0WW to power 4-Slot MC30/MC31/MC32 Legacy Cradles.</li> </ul>	
CBL-DC-380A1-01		4-Way Power Cable	<ul style="list-style-type: none"> <li>Used with Power Supply PWR-BGA12V108W0WW to power up to four MC33 4-Slot Battery Chargers (SAC-MC33-4SCHG-01).</li> </ul>	
PWR-BGA12V108W0WW		Power Supply	<ul style="list-style-type: none"> <li>Used to power 4-Slot Cradles, 5-Slot Cradles, and 20-Slot MC33 Spare Battery Charger.</li> <li>100-240 VAC, 12V, 9A, 108W</li> <li>Provides US DOE Level VI compliance for power efficiency.</li> <li>Replaces PWRS-14000-241R</li> </ul>	CBL-DC-382A1-01 and 23844-00-00R
23844-00-00R		AC Line Cord		
50-16000-182R		AC Line Cord	Used with 50-14000-147R/50-14000-249R/PWRS-14000-249R/PWR-BUA5V16W0WW	
PWR-WUA5V12W0US (US plug style) PWR-WUA5V12W0GB (UK plug style) PWR-WUA5V12W0EU (EU plug style) PWR-WUA5V12W0AU (Australia plug style) PWR-WUA5V12W0CN (China plug style) PWR-WUA5V12W0IN (India plug style)		USB Power Supply	<ul style="list-style-type: none"> <li>Used with MC33 Charge/Communication Cable (CBL-MC33-USBCHG-01) to charge device.</li> <li>Provides higher current (2.5A) for faster charging</li> <li>100-240 VAC, 5 V, 2.5 A</li> </ul>	
<b>Batteries</b>				
<b>Part Number</b>	<b>Picture</b>	<b>Description</b>	<b>Notes</b>	<b>Required Items</b>

<p>BTRY-MC33-27MA-01 (single)  BTRY-MC33-27MA-10 (10 pack)    BTRY-MC33-27MA-IN (for use in India)</p>		<p>MC33 Spare Standard Capacity Battery with PowerPrecision Plus (2740 mAh)</p> 	<ul style="list-style-type: none"> <li>•Designed, manufactured &amp; tested to meet rigorous controls &amp; standards</li> <li>•Premium-grade cells with higher capacity &amp; longer life cycle</li> <li>•Designed to help prevent overcharging &amp; electrical shock</li> <li>•Strong &amp; robust housing for optimal performance &amp; durability</li> <li>•Information available: <ul style="list-style-type: none"> <li>- Advanced state of Charge (shows the remaining battery power based on two factors: present charge and present real-time usage patterns of the device).</li> <li>- Advanced State of Health (highly accurate end-of-life prediction)</li> <li>- Dynamic usage patterns are constantly calculated, factoring in criteria such as the applications that are in use and scanning frequency).</li> </ul> </li> <li>•Only compatible with MC33, except MC33 RFID units.</li> </ul>	
<p>BTRY-MC33-52MA-01 (single)  BTRY-MC33-52MA-10 (10 pack)    BTRY-MC33-52MA-IN (for use in India)</p>		<p>MC33 Spare High Capacity Battery with PowerPrecision Plus (5200 mAh)</p> 	<ul style="list-style-type: none"> <li>•Designed, manufactured &amp; tested to meet rigorous controls &amp; standards</li> <li>•Premium-grade cells with higher capacity &amp; longer life cycle</li> <li>•Designed to help prevent overcharging &amp; electrical shock</li> <li>•Strong &amp; robust housing for optimal performance &amp; durability</li> <li>•Information available: <ul style="list-style-type: none"> <li>- Advanced state of Charge (shows the remaining battery power based on two factors: present charge and present real-time usage patterns of the device).</li> <li>- Advanced State of Health (highly accurate end-of-life prediction)</li> <li>- Dynamic usage patterns are constantly calculated, factoring in criteria such as the applications that are in use and scanning frequency).</li> </ul> </li> <li>•Only compatible with MC33, including MC33 RFID units.</li> </ul>	
<p>BTRY-MC3XKAB0E  BTRY-MC3XKAB0E-10 (10 pack)  BTRY-MC3XKAB0E-50 (50 pack)</p>		<p>MC3000/MC3100 Spare 1X Battery (2740 mAh)</p>	<ul style="list-style-type: none"> <li>•Compatible with MC3000 or MC3100 units</li> <li>•Works on Straight Shooter and Rotating Head configuration units only.</li> </ul>	
<p>BTRY-MC32-01-01  BTRY-MC32-01-10 (10 pack)</p>		<p>MC3200 Spare 1X Battery with PowerPrecision (2740 mAh)</p> 	<ul style="list-style-type: none"> <li>•Works with all MC32XX configurations only</li> <li>•Supports PowerPrecision battery management application</li> <li>•Also compatible with MC33, except MC33 RFID units.</li> </ul>	
<p>BTRY-MC31KAB02  BTRY-MC31KAB02-10 (10 pack)</p>		<p>MC3100 Spare 2X High Capacity Battery (4800 mAh)</p>	<ul style="list-style-type: none"> <li>•Works with all MC31XX configurations only</li> <li>•Does not use pull tab</li> </ul>	

<p>BTRY-MC32-52MA-01</p> <p>BTRY-MC32-52MA-10 (10 pack)</p>		<p>MC3200 Spare 2X High Capacity Battery with PowerPrecision (5200 mAH)</p>	<ul style="list-style-type: none"> <li>•Works with MC32xx configurations only</li> <li>•Supports PowerPrecision battery management application</li> <li>•Also compatible with MC33, including RFID units.</li> </ul>	
<p>KT-128373-01R</p>		<p>MC31xx Brick or Turret Head 2X Battery Door</p>	<ul style="list-style-type: none"> <li>•Only includes 2x battery door (no handstrap or stylus)</li> </ul>	
<p>KT-128374-01R</p>		<p>MC31xx Gun 2X Battery Door</p>	<ul style="list-style-type: none"> <li>•Only includes 2x battery door (no handstrap or stylus)</li> </ul>	